



## **Application Note**

### **AN232B-03**

# **Optimizing D2XX Data Throughput**

**Version 1.2**

**Issue Date: 18-03-2024**

This application note provides guidelines for achieving optimal performance over USB from D2XX applications.

Use of FTDI devices in life support and/or safety applications is entirely at the user's risk, and the user agrees to defend, indemnify, and hold FTDI harmless from any and all damages, claims, suits, or expense resulting from such use.

**Future Technology Devices International Limited (FTDI)**  
Unit 1, 2 Seaward Place, Glasgow G41 1HH, United Kingdom  
Tel.: +44 (0) 141 429 2777 Fax: + 44 (0) 141 429 2758  
Web Site: <http://ftdichip.com>

Copyright © Future Technology Devices International Limited

## **Table of Contents**

<b>1 Introduction .....</b>	<b>3</b>
<b>2 Optimizing Data Throughput Over USB .....</b>	<b>3</b>
<b>2.1 Transfer Sizes .....</b>	<b>3</b>
<b>2.2 Driver Operation.....</b>	<b>3</b>
<b>2.3 Optimizing Performance.....</b>	<b>3</b>
<b>3 Contact Information .....</b>	<b>5</b>
<b>Appendix A – References .....</b>	<b>6</b>
<b>Document References .....</b>	<b>6</b>
<b>Acronyms and Abbreviations.....</b>	<b>6</b>
<b>Appendix B – List of Tables and Figures.....</b>	<b>7</b>
<b>List of Tables.....</b>	<b>7</b>
<b>List of Figures .....</b>	<b>7</b>
<b>Appendix C – Revision History .....</b>	<b>8</b>

## 1 Introduction

This application note provides guidelines for achieving optimal performance over USB from D2XX applications.

## 2 Optimizing Data Throughput Over USB

### 2.1 Transfer Sizes

The maximum transfer size over USB is setup once and for all when a device is initialized. An application can change the current USB transfer size to a value not exceeding the maximum USB transfer size. The best transfer size for an application depends on its type.

For example, an application that handles streaming data will run more efficiently with a large transfer size, whereas a smaller transfer size may be more suited to an application that handles small amounts of data.

### 2.2 Driver Operation

In the D2XX device driver, the maximum USB transfer size is set at 64Kbytes. This is necessary to support USB2.0 controllers: on USB2.0, we have found that transfer sizes greater than 64K fail catastrophically.

Current USB transfer size can be changed using the function `FT_SetUSBParameters`. The change comes into effect immediately, and any data that was held in the driver at the time of the change is lost.

Note that, currently, `FT_SetUSBParameters` supports transfer size changes for the IN endpoint only, and the remainder of this note is restricted to consideration of read requests.

When a device is opened, the driver allocates two buffers: a USB transfer buffer of maximum USB transfer size bytes and a read buffer whose size is based on, but not the same as, the maximum USB transfer size. The current USB transfer size is set by default to 4Kbytes, but an application may setup the current USB transfer size any time after a device has been opened. The driver performs USB requests of any size up to the current USB transfer size, then copies the data to the read buffer. The actual USB request size is determined by the space that is currently available in the read buffer. If the read buffer becomes full (i.e. there is not enough space in the read buffer to hold data returned from a USB request), the driver will stop issuing USB requests until space becomes available.

Data is removed from the read buffer when the application performs a read request. So, the rate at which the application issues read requests has a direct bearing on the driver's ability to keep issuing USB requests. USB requests will continue to be issued as long as the application performs enough read requests to ensure that the read buffer does not become full.

### 2.3 Optimizing Performance

The question of how-to setup an application for optimized data throughput is complicated by the format of the data that is transferred over USB. Data is transferred over USB in a series of 64-byte packets. Each packets contains 2 bytes that are reserved by FTDI and 62 bytes of actual data. So, a 4Kbyte USB transaction contains 3968 bytes of actual data, and a 64Kbyte transaction contains 63488 bytes. In general, an x byte USB transaction yields  $x - ((x/64) * 2)$  bytes of actual data.

Optimized throughput occurs when the maximum amount of data is transferred in the least possible number of USB transactions. The necessary condition is that the application's request size must be matched to the current USB request size. More precisely, optimal throughput is achieved when the application request size is a multiple of the number of actual data bytes contained in the current USB transfer size. For example, using a current USB transfer size of 4Kbytes, optimal throughput is achieved with application request sizes that are multiples of 3968 bytes.

---



Maximum throughput is achieved using a current USB transfer size of 64Kbytes, and application requests that are multiples of 63448 bytes.

### 3 Contact Information

#### Head Office – Glasgow, UK

Future Technology Devices International Limited (UK)  
Unit 1, 2 Seaward Place, Centurion Business Park  
Glasgow G41 1HH  
United Kingdom  
Tel: +44 (0) 141 429 2777  
Fax: +44 (0) 141 429 2758

E-mail (Sales) [sales1@ftdichip.com](mailto:sales1@ftdichip.com)  
E-mail (Support) [support1@ftdichip.com](mailto:support1@ftdichip.com)  
E-mail (General Enquiries) [admin1@ftdichip.com](mailto:admin1@ftdichip.com)

#### Branch Office – Tigard, Oregon, USA

Future Technology Devices International Limited (USA)  
7130 SW Fir Loop  
Tigard, OR 97223-8160  
USA  
Tel: +1 (503) 547 0988  
Fax: +1 (503) 547 0987

E-mail (Sales) [us.sales@ftdichip.com](mailto:us.sales@ftdichip.com)  
E-mail (Support) [us.support@ftdichip.com](mailto:us.support@ftdichip.com)  
E-mail (General Enquiries) [us.admin@ftdichip.com](mailto:us.admin@ftdichip.com)

#### Branch Office – Taipei, Taiwan

Future Technology Devices International Limited (Taiwan)  
2F, No. 516, Sec. 1, NeiHu Road  
Taipei 114  
Taiwan, R.O.C.  
Tel: +886 (0) 2 8797 1330  
Fax: +886 (0) 2 8751 9737

E-mail (Sales) [tw.sales1@ftdichip.com](mailto:tw.sales1@ftdichip.com)  
E-mail (Support) [tw.support1@ftdichip.com](mailto:tw.support1@ftdichip.com)  
E-mail (General Enquiries) [tw.admin1@ftdichip.com](mailto:tw.admin1@ftdichip.com)

#### Branch Office – Shanghai, China

Future Technology Devices International Limited (China)  
Room 1103, No. 666 West Huaihai Road,  
Shanghai, 200052  
China  
Tel: +86 (21) 62351596  
Fax: +86 (21) 62351595

E-mail (Sales) [cn.sales@ftdichip.com](mailto:cn.sales@ftdichip.com)  
E-mail (Support) [cn.support@ftdichip.com](mailto:cn.support@ftdichip.com)  
E-mail (General Enquiries) [cn.admin@ftdichip.com](mailto:cn.admin@ftdichip.com)

#### Web Site

<http://ftdichip.com>

#### Distributor and Sales Representatives

Please visit the Sales Network page of the [FTDI Web site](#) for the contact details of our distributor(s) and sales representative(s) in your country.

System and equipment manufacturers and designers are responsible to ensure that their systems, and any Future Technology Devices International Ltd (FTDI) devices incorporated in their systems, meet all applicable safety, regulatory and system-level performance requirements. All application-related information in this document (including application descriptions, suggested FTDI devices and other materials) is provided for reference only. While FTDI has taken care to assure it is accurate, this information is subject to customer confirmation, and FTDI disclaims all liability for system designs and for any applications assistance provided by FTDI. Use of FTDI devices in life support and/or safety applications is entirely at the user's risk, and the user agrees to defend, indemnify, and hold harmless FTDI from any and all damages, claims, suits, or expense resulting from such use. This document is subject to change without notice. No freedom to use patents or other intellectual property rights is implied by the publication of this document. Neither the whole nor any part of the information contained in, or the product described in this document, may be adapted, or reproduced in any material or electronic form without the prior written consent of the copyright holder. Future Technology Devices International Ltd, Unit 1, 2 Seaward Place, Centurion Business Park, Glasgow G41 1HH, United Kingdom. Scotland Registered Company Number: SC136640

## Appendix A – References

### Document References

N/A

### Acronyms and Abbreviations

Terms	Description
USB	Universal Serial Bus

## **Appendix B – List of Tables and Figures**

### **List of Tables**

N/A

### **List of Figures**

N/A

## Appendix C – Revision History

Document Title: AN232B-03 Optimizing D2XX Data Throughput  
Document Reference No.: FT\_001568  
Clearance No.: FTDI#596  
Product Page: <https://ftdichip.com/>  
Document Feedback: [Send Feedback](#)

Revision	Changes	Date
1.0	Initial release	03-2004
1.1	Format and contact information updated. Release version on the web	02-2006
1.2	Updated release version.	18-03-2024